



Features

- 8 in 1 Out RF combiner
- 1U Rack mount
- Low insertion loss, high return loss and isolation
- High quality
- Durable, Reliable and Flexible

8 Ways RF Combiner CMB-8

Specifications

Model		CMB-8
Insertion Loss OUT-IN	5-240MHz	10.5 dB(Max)
	240-470MHz	11.0 dB(Max)
	470-750MHz	11.5 dB(Max)
	750-1000MHz	12.5 dB(Max)
Isolation Loss IN-IN	5-240MHz	28 dB(Min)
	240-470MHz	30 dB(Min)
	470-750MHz	28 dB(Min)
	750-1000MHz	25 dB(Min)
Return Loss IN/OUT	5-240MHz	16 dB(Min)
	240-470MHz	16 dB(Min)
	470-750MHz	16 dB(Min)
	750-1000MHz	16 dB(Min)
General Information	Interface / Impedance	F, 75Ω

SPECIFICATIONS SUBJECT TO CHANGE WITHOUT NOTICE.